

RE-500P Series

Addressable Manual Pull Station

General

RE-500P series addressable pull stations are wall-mounted devices that are located near the exit doors to allow the passers-by to manually trigger. It is a dual action pull station (i.e.) it requires two motions to activate, user has to lift the flap and push the handle for activation.

The addressable Manual Pull Station has inbuilt isolator with polarity sensitive terminals for external wiring. The address for this device shall be configured by using the 8-way DIP switch. The red blinking LED indicates normal operating condition and the steady state for activated condition. RE-500P series has 4 variants with respect to the application like Fire, Release, Abort & Emergency release in Red, Green, Yellow & Blue colours and these devices are working with contact monitoring.



Features

- Complies UL 38 8th edition.
- DIP Switches for addressing.
- Address ranges from 1 to 250.
- Inbuilt isolator.
- SLC communication with the panel.
- Lift and push.
- Status indicator.
- Key lock access.
- Low Standby Current.


Construction Material

- Light weight FR-ABS housing.
- Terminal block (4 Position).

Specification


Electrical Specification	Addressable
<i>Operating Voltage</i>	17 - 32 VDC
<i>Standby Current</i>	0.5 mA
<i>Alarm Current</i>	2 mA
<i>Switch Contact Rating</i>	500mA (Max)
<i>Operating Temperature</i>	0 – 49°C
<i>Storage Temperature</i>	0 – 60°C
<i>Relative Humidity</i>	0 - 93% RH non-condensing
<i>IP Rating</i>	IP 40
<i>Connection</i>	2.5mm ² Max (12AWG)
<i>Dimension (inches / mm)</i>	5.5L x 4.1W x 1.1D / 140L X 105W X 29D
<i>Weight</i>	125g Approx
<i>Material</i>	FR - ABS
<i>Colour</i>	Red, Blue, Yellow, Green

Dimensions



Wiring Diagram

The wiring terminal accepts solid or stranded cables up to 2.5 mm². Connect the pull station to positive & negative terminal, observing the polarity.



Compatible Devices

Models	Description
AARAL X4	Analogue Addressable Fire Alarm Control Panel expandable upto 4 loops
AARAL X8	Analogue Addressable Fire Alarm Control Panel expandable upto 8 loops

Ordering Information

Models	Description
RE-558P-R	Addressable pull station – Red - Alarm
RE-559P-G	Addressable pull station – Green - Release
RE-559P-Y	Addressable pull station – Yellow - Abort
RE-560P-B	Addressable pull station – Blue – Door Release

India

RAVEL ELECTRONICS PVT LTD.,
150A, Electronics Industrial Estate,
Perungudi, Chennai – 96, India.
E-mail: sales@ravelfire.com; Web: www.ravelfire.com

UAE

RAVEL DMCC,
Unit No: G30, DMCC Business Center,
Level No 13, AG Tower, Dubai, UAE.
E-mail: sales@raveldmcc.com

USA

RAVEL AMERICAS INC.,
2855 NW 112th Ave ST#2 Miami,
Doral, Florida 33172, USA.
E-mail: sales.us@ravelfire.com